



**DEVELOPMENT OF NEW TWO
DIMENSIONAL FCC-MDW CODE WITH
WAVELENGTH/TIME SCHEME IN OPTICAL
CODE DIVISION MULTIPLE ACCESS
(OCDMA) NETWORK SYSTEMS**

by

**NUI A/P DIN KERAF
(1340811099)**

A thesis submitted in fulfilment of the requirements for the degree of
Doctor of Philosophy in Communication Engineering

**School of Computer and Communication Engineering
UNIVERSITI MALAYSIA PERLIS**

2017

UNIVERSITI MALAYSIA PERLIS

DECLARATION OF THESIS

Author's full name : NUI A/P DIN KERAF
Date of Birth : 17-09-1972
Title : DEVELOPMENT OF NEW TWO DIMENSIONAL FCC-
MDW CODE WITH WAVELENGTH/TIME SCHEME IN
OPTICAL CODE DIVISION MULTIPLE ACCESS
(OCDMA) NETWORK SYSTEMS
Academic Session : Semester I – 2017

I hereby declare that the thesis becomes the property of Universiti Malaysia Perlis (UniMAP) and to be placed at the library of UniMAP. This thesis is classified as:

CONFIDENTIAL (Contains confidential information under the Official Secret Act 1972)*

RESTRICTED (Contains restricted information as specified by the organization where research was done)*

OPEN ACCESS I agree that the thesis is to be made immediately available as hard copy or on-line open access (full text)

I, the author, give permission to the UniMAP to produce this thesis in whole or in part for the purpose of research or academic exchange only (except during a period of _____ years, of so requested above).

Certified by:

SIGNATURE

720917-09-5044

NEW IC NO. / PASSPORT NO.)

Date: _____

SIGNATURE OF SUPERVISOR

PROF. DR. SYED ALWEE ALJUNID
SYED JUNID

NAME OF SUPERVISOR

Date: _____

NOTES: * If the thesis is CONFIDENTIAL or RESTRICTED, please attach with the letter from the organization with period and reasons for confidentiality or restriction.

ACKNOWLEDGEMENT

Firstly, I would like to express the deepest appreciation to my main supervisor, Dean of Research, Management and Innovation Centre, Universiti Malaysia Perlis, Professor Dr. Syed Alwee Aljunid Syed Junid for his valuable guidance, inspiring advice and continual encouragement as well as support at all stages of this thesis work.

I owe my deepest gratitude to my late co-supervisor, Dr Amir Razif Arief Jamil Abdullah for valuable discussions especially during the initial stage of this research. I would like to thank my co-supervisor, Prof. Madya Dr Ir Anuar Mat Safar and Dr Mohd Rashidi Che Beson for the guidance, advice and motivation.

I am indebted to my friend and colleague, Nurolhuda Mohd Noor, who always encouraged me to overcome all obstacles during this study. Additionally, a thank you to the funding provided by the Ministry of Higher Education who gives me a chance to make my dream comes true.

Last but not least, my profound love and deepest gratitude my beloved family; late parents, parents-in-law for their constant support and kindness at every stage of my life. Also, my special thanks to my husband – Dr. Phaklen Ehkan, my children - Sarayuth Prommanop, Saranyaa Prommanop, Sara Suphamaard Prommanop and Sara Suphattra Prommanop for their unreserved love, support and always behind me throughout my study and exhausted time.

TABLE OF CONTENTS

	Page
THESIS DECLARATION	i
ACKNOWLEDGEMENT	ii
TABLE OF CONTENTS	iii
LIST OF TABLES	vii
LIST OF FIGURES	viii
LIST OF ABBREVIATIONS	xiii
LIST OF SYMBOLS	xv
ABSTRAK	xvii
ABSTRACT	xviii
CHAPTER 1 INTRODUCTION	1
1.1 Demand for OCDMA Technology	1
1.2 Problem Statement	2
1.3 Research Objectives	4
1.4 Scope of Works	4
1.5 Research Contribution	5
1.6 Thesis Structure	6
CHAPTER 2 LITERATURE REVIEW	8
2.1 Introduction	8
2.2 Multiple Access Techniques	11
2.2.1 Wavelength Division Multiple Access	12
2.2.2 Time Division Multiple Access	13
2.2.3 Code Division Multiple Access	16
2.3 Evolution of OCDMA Technology	20
2.4 Classification of OCDMA System	28
2.4.1 Coherent OCDMA Schemes	29
2.4.1.1 Temporal Phase Encoding OCDMA	30
2.4.1.2 Spectral Phase Encoding (SPC) OCDMA	32
2.4.2 Incoherent OCDMA Schemes	34

2.4.2.1	Temporal Spreading Encoding OCDMA	36
2.4.2.2	Spectral Amplitude Encoding (SAC) OCDMA	38
2.4.2.3	Spread Space Coding or Two-Dimensional Spatial Encoding OCDMA	40
2.4.2.4	Hybrid Encoding OCDMA	42
2.5	OCDMA Detection Techniques	46
2.5.1	Direct Detection Technique	47
2.5.2	Complementary Subtraction Technique	48
2.5.3	AND Subtraction Technique	50
2.6	Optical Detectors	51
2.6.1	PIN Photodiode	52
2.6.2	Avalanche Photodiode (APD)	53
2.7	Major Challenges in OCDMA Systems	55
2.8	Summary	57
 CHAPTER 3 RESEARCH METHODOLOGY		59
3.1	Introduction	59
3.2	Method of Designing Two-Dimensional Incoherent OCDMA Codes	62
3.3	Parameter to Analyse the Performance of Two Dimensional Code	67
3.3.1	Multiple Access Interference (MAI)	67
3.3.2	Noise Consideration	70
3.3.2.1	Phase Induced Intensity Noise (PIIN)	70
3.3.2.2	Shot Noise	72
3.3.2.3	Thermal Noise	72
3.3.3	Signal to Noise Ratio and Bit Error Rate	73
3.3.4	Modulation Format or Coding Scheme	75
3.3.5	Simulation Analysis	77
3.4	Summary	78

CHAPTER 4 TWO-DIMENSIONAL WAVELENGTH/TIME FCC-MDW CODE DESIGN	79
4.1 Introduction	79
4.2 Construction of Two-Dimensional FCC-MDW Code	81
4.2.1 Formulation of Cross Correlation Properties for Two -Dimensional FCC MDW Code	83
4.3 Two-Dimensional FCC-MDW Encoder and Decoder System Design	92
4.3.1 The Encoder Design of 2-D FCC-MDW	93
4.3.2 The Decoder Design of 2-D FCC-MDW	98
4.4 Formulation of Signal to Noise Ratio and Bit Error Rate for 2-D FCC MDW	100
4.5 Formulation of Signal to Noise Ratio and Bit Error Rate for 2-D FCC MDW for Avalanche Photodiode (APD).	113
4.6 Summary	115
CHAPTER 5 PERFORMANCE EVALUATION OF TWO- DIMENSIONAL WAVELENGTH/TIME FCC-MDW CODE IN OCDMA SYSTEM NETWORK	117
5.1 Introduction	117
5.2 Theoretical Analysis of Two Dimensional FCC- MDW	118
5.2.1 The Effect of Number of Simultaneous Users on the System Performance Considering Total Noise	119
5.2.2 The Effect of Effective Power (P_{sr}) on System Performance Considering Total Noise	122
5.2.3 The Effect of Number of Simultaneous Users on PIIN and Shot Noise	123
5.2.4 The Effect of Effective Power (P_{sr}) on PIIN and Shot Noise System Performance	127
5.2.5 The Relationship of Multiple Bit Rate on System Performance	130
5.2.6 The Relationship of Varying Hamming Weight on the System Performance	135
5.2.7 The Effects of Different Wavelength and Time Spreading on the Cardinality of the System	137
5.2.8 The Effects of Different Wavelength and Time Spreading	141

on the Data Rates.	
5.2.9 The Effect of PIN and APD on 2-D FCC-MDW System Performance	142
5.2.10 The Effect of APD Photo detector on Cardinality based on PIIN and Shot Noise	145
5.2.11 The Effect APD Gain on System Performance	148
5.2.12 The Effect of APD on the System's Effective Power (Psr)	149
5.2.13 The Effect of APD on System's Data Rate	150
5.3 Simulation Analysis of Two-dimensional FCC- MDW	151
5.3.1 Effect of Power on 2-D FCC-MDW Performance	158
5.3.2 Effect of Fiber Distance on System Performance.	160
5.3.3 Effect of Chip Width on 2-D FCC-MDW Performance.	161
5.4 Comparison between Simulation and Theoretical Results	164
5.5 Summary	165
6 CONCLUSION AND FUTURE WORK	167
6.1 Conclusion	167
6.2 Recommendations for Future Work	170
REFERENCES	171
LIST OF PUBLICATIONS	183

LIST OF TABLES

NO.		PAGE
2.1	Types and characteristics of encoding approaches used in the OCDMA systems.	45
2.2	Characteristics of common PIN photodiodes	53
2.3	Characteristics of common APD photodiodes	55
3.1	General principle for designing the incoherent OCDMA system	65
4.1	Two-dimensional FCC-MDW code sequences with $k_1 = 4, k_2 = 2$	82
4.2	Cross Correlation of 2-D FCC-MDW code. (a) in terms of numbers and (b) in terms of k_1 and k_2	89
4.3	Wavelengths assignment for two-dimensional FCC-MDW code sequences.	95
5.1	Parameters used in the Mathematical Calculation	118
5.2	Comparison of 2-D OCDMA spectral efficiencies	135
5.3	Parameters used in Mathematical Calculation for APD	144
5.4	Comparison of noise spectral density associated with noise components for 2-D FCC-MDW PIN and APD	148

LIST OF FIGURES

NO.		PAGE
2.1	Scheme of an optical fiber communication system	8
2.2	Simple block diagram of WDM system	12
2.3	WDMA system	13
2.4	TDMA system	14
2.5	Schematic of a general OTDMA systems using optical pulse laser sources	15
2.6	Conversation analogy for CDMA system	17
2.7	The relation of OCDMA to WDMA and TDMA	18
2.8	The classification of OCDMA	29
2.9	(a) Two temporal phase codes (b) Temporal phase coding using fiber delay lines and optical phase modulators	31
2.10	(a) Principle of Spectral phase coding and (b) structure of spectral phase coding.	33
2.11	Encoding in OCDMA (a) data bit 1010 and (b) transmitted sequences 10101.	35
2.12	(a) Two temporal spreading codes (b) Method for Implementation of the code sequences shown in (a)	36
2.13	Principle of SAC-OCDMA	39
2.14	Block diagram of the proposed OCDMA system based upon spatial spread spectrum	41
2.15	(a) The examples of code sequences for WHTS OCDMA. (b) Implementation of a WHTS OCDMA encoder using AWGs and (c) using an array of FBGs	43
2.16	Direct detection technique	47

2.17	Complementary subtraction technique	48
2.18	AND subtraction technique	50
2.19	Typical silicon P-I-N diode schematic	52
2.20	Avalanche photodiode (APD)	54
3.1	Classification of proposed 2-D OCDMA code	61
3.2	Schematic of encoding of 2-D wavelength-time code	63
3.3	A typical wavelength-time OCDMA network	64
3.4	Auto correlation and cross-correlation peaks	68
3.5	Noise components coming to the receiver front end	71
3.6	NRZ and RZ coding	76
4.1	Flowchart of development and the analysis of 2-D FCC-MDW	80
4.2	An example of 2-D FCC-MDW signature codes	83
4.3	An elements of (a) characteristic matrix $A^{(0)}$ and (b) $A_{g,h}$ of 2-D FCC-MDW code.	85
4.4	An elements of $A^{(1)}$, $A^{(2)}$ and $A^{(3)}$ for 2-D FCC-MDW code	88
4.5	Schematic of 2-D FCC-MDW W/T OCDMA network	93
4.6	Structure of 2-D FCC-MDW transmitter	94
4.7	Codes simplification for 2-D FCC-MDW code at the encoder for (a) the time slot t_2 is ignored and considered t_1 as a delay and (b) the time slot t_0 is ignored and considered t_2 as a delay.	97
4.8	Codes simplification for 2-D FCC-MDW code with two groups of time delay	98
4.9	Structure of 2-D FCC-MDW receiver	99
4.10	The relationship of coherence time and spectral density of two random waves	103
5.1	BER against the number of simultaneous users for 2-D FCC-MDW, 1-D FCC and 1-D MDW codes	120

5.2	BER against the number of simultaneous users for 2-D FCC-MDW, 1-D codes and other 2-D OCDMA codes	121
5.3	BER against the effective power, P_{sr} for 2-D FCC-MDW, 2-D DPD and 2-D PD codes	122
5.4	Variations of PIIN power for different 2-D OCDMA codes with fixed P_{sr} at -10dBm.	124
5.5	Variations of shot noise power for different 2-D OCDMA codes with fixed P_{sr} at -10dBm	124
5.6	Variations of the total PIIN power and shot noise power for different 2-D OCDMA codes with fixed P_{sr} at -10dBm.	125
5.7	The comparison of PIIN, shot and thermal noises on the performance of 2-D FCC-MDW code.	126
5.8	The PIIN and shot noise power against the effective power, P_{sr} for 2-D FCC-MDW, 2-D W/T MQC/MQC and 2-D PD codes.	128
5.9	The sum of PIIN and shot noise power against the effective power, P_{sr} for 2-D FCC-MDW, 2-D W/T MQC/MQC and 2-D PD codes.	129
5.10	(a) BER against the number of simultaneous users for 2-D FCC-MDW, 2-D PD and 2-D DPD codes at bit rate 0.622Gbps	130
	(b) BER against the number of simultaneous users for 2-D FCC-MDW, 2-D PD and 2-D DPD codes at bit rate 1.0 Gbps.	131
	(c) BER against the number of simultaneous users for 2-D FCC-MDW, 2-D PD and 2-D DPD codes at bit rate 2.5 Gbps	131
5.11	BER against the data rates for 2-D FCC-MDW, 2-D PD and 2-D DPD codes.	133
5.12	Performance of BER against the number of simultaneous users for variations of Hamming weight (HW) and code size of 2-D FCC-MDW.	136
5.13	Performance of BER against the number of simultaneous users for 2-D FCC-MDW with the different number of wavelength, M and time spreading, N.	138
5.14	(a) Performance of BER against the number of simultaneous users for 2-D FCC-MDW with the fixed value of time spreading, N	139

5.14	(b) Performance of BER against the number of simultaneous users for 2-D FCC-MDW with the fixed number of wavelength, M.	140
5.15	BER against the data rates for variations of 2-D FCC-MDW codes.	141
5.16	Performance of BER against the number of simultaneous users for 2-D FCC-MDW for PIN and APD Photodetector	144
5.17	The System Performance using APD PIIN and Shot Noise against the number of simultaneous users for 2-D FCC-MDW	146
5.18	The APD PIIN and Shot Noise Power against the number of simultaneous users for 2-D FCC-MDW.	146
5.19	Performance of BER against the number of simultaneous users for 2-D FCC-MDW with variations of APD Gain	148
5.20	Performance of BER against the effective power for 2-D FCC-MDW with variations of APD Gain.	150
5.21	Performance of BER against the data rates for 2-D FCC-MDW with variations of APD Gain	151
5.22	The general simulation design of 2-D FCC-MDW OCDMA	152
5.23	The optical spectrum with the bandwidth 8nm used in the simulation	152
5.24	The simulation wavelength components for User#1 with the code weight, $k_1 = 4$.	153
5.25	(a) The simulation, layout for part of transmitter side	155
5.25	(b) The simulation layout for the transmission medium.	156
5.25	(c) The simulation layout for receiver side of User#1	157
5.26	BER versus the effective power for variations of data rates	158
5.27	Q-Factor versus the effective power for variations of data rates	159
5.28	BER versus the fiber length for variations of data rates	160
5.29	Q-Factor versus the fiber length for variations of data rates	161
5.30	Eye diagram with the data rates of 0.622 Gbps and 10km fiber length for chip width at (a) 0.1 nm,	162

5.30	Eye diagram with the data rates of 0.622 Gbps and 10km fiber length for chip width at (b) 0.5nm	163
5.30	Eye diagram with the data rates of 0.622 Gbps and 10km fiber length for chip width at (c) 0.8nm	163
5.31	BER versus the effective power for 2-D FCC-MDW for theoretical and simulation results	164

©This item is protected by original copyright

LIST OF ABBREVIATIONS

APD	Avalanche Photodiode
ASE	Amplified Spontaneous Emission
BER	Bit Error Rate
BLS	Broadband Light Source
CDMA	Code division multiple access
DCS	Dynamic Cyclic Shift
DPD	Diluted Perfect Difference
DS	Direct-Sequence
DW	Double Weight
EDFA	Erbium Doped Fibre Amplifier
FBG	Fiber Bragg Grating
FH	Frequency Hopping
FTTH	Fiber-to-the Home
FTTB	Fiber-to-the-Building
FTTC	Fiber-to-the-Curb
LAN	Local Area Network
LED	Light emitting diode
MAI	Multiple Access Interference
MDW	Modified Double Weight
MMC	M-Matrices Code
MQC	Modified Quadratic Congruence
NRZ	Non return-to-zero
OCDMA	Optical CDMA
OOK	ON-OFF Keying
OTDMA	Optical Time Division Multiple Access

PDC	Perfect Difference Code
PIIN	Phase Induced Intensity Noise
PLCs	planar lightwave circuits
PONs	Passive Optical Network
PSD	Power Spectral Density
QoS	Quality of Service
SAC	Spectral Amplitude Coding
SMF	Single Mode Fiber
SNR	Signal to Noise ratio
SPE	Spectral Phase encoding
SSFBG	Super-structured fiber Bragg gratings
TOFDLs	Tunable Optical Fiber Delay lines
TPE	Temporal Phase encoding
WDM	Wavelength Division Multiplexing
WDMA	Wavelength Division Multiple Access
WHTS	Wavelength Hopping Time Spreading
W/T	Wavelength/Time
ZCC	Zero Cross Correlation
1-D	One-dimensional
2-D	Two-dimensional

LIST OF SYMBOLS

Code Weight	w
2-D FCC-MDW code weight	k_1, k_2
Power spectral density of the pulse	$S(f)$
Effective ionization ratio of the APDs	K_{eff}
Responsivity	\mathfrak{R}
Excess Noise Factor of APD	F
Optimum APD gain	G
Number of Users	K
2-D FCC-MDW number of user	W
Code length	N
Spectral Width	Δv
Bandwidth of the source	Δf
Bit of data for the w th user	$d(w)$
Cross-correlation	λ_c
Auto –correlation	λ_a
Number of wavelength	M
Spectral encoding	X_g
Spatial encoding	Y_h
Average photocurrent	I
Electrical Bandwidth	B
Coherence time	τ_c
Electron charge	e
Boltzman’s constant	K_b
Absolute receiver noise temperature	T_n

Receiver load resistor	R_L
Central frequency	f_0
Effective power of a broadband source at the receiver	P_{sr}
Unit step function	$u(f)$
Noise equivalent electrical bandwidth of the receiver	B_r
Optical received power	P_r
Data transmission rate	R_b

©This item is protected by original copyright

Pembangunan Baru Kod Dua Dimensi FCC-MDW Dengan Skim Panjang Gelombang/Masa dalam Sistem Rangkaian Akses Pelbagai Pembahagian Kod Optik (OCDMA)

ABSTRAK

Peningkatan secara besar-besaran khususnya daripada pengguna internet di seluruh dunia menggalakkan pembekal perkhidmatan bersama-sama dengan para penyelidik untuk meneroka teknologi telekomunikasi yang sesuai dan bermanfaat kepada pengguna. Unikinya, berbanding dengan teknik akses pelbagai yang lain, teknik Akses Pelbagai Pembahagian Kod (OCDMA) boleh digunakan dalam rangkaian akses optik dengan perkhidmatan mengikut permintaan, seperti protokol internet, video atas permintaan, tele-kehadiran dan audio berkualiti tinggi. Walaupun terdapatnya keutuhan di dalam OCDMA, kewujudan gangguan capaian pelbagai (MAI) dan hingar fasa intensiti teraruh (PIIN) dalam sistem menjejaskan prestasinya. Malah, MAI terkenal sebagai faktor utama kemerosotan prestasi dalam sistem OCDMA itu. Atas alasan tersebut, di dalam tesis ini, siasatan telah dijalankan untuk meneroka kod tersendiri yang boleh mengurangkan MAI dan PIIN. Motivasi lain kajian ini adalah untuk mendapatkan kod tersendiri yang boleh menampung sejumlah besar pengguna serentak yang selaras dengan tuntutan semasa. Maka, kod dua dimensi (2-D) fleksibel korelasi silang- berat berganda diubahsuai (FCC-MDW) dengan skim panjang gelombang/masa (W/T) dicadangkan dan didemonstrasikan. Pada asasnya, pembangunan kod 2-D FCC-MDW dibentuk dengan menggabungkan dua kod satu dimensi (1-D) OCDMA yang dikenali sebagai kod 1-D FCC dan 1-D MDW. Pembangunan kod bermula dengan menetapkan kod 1-D MDW sebagai corak gelombang pengekodan dan urutan kod 1-D FCC sebagai corak penyebaran masa. Lebih lagi, dalam usaha untuk mengurangkan MAI, pengekod dan penyahkod baru 2-D FCC-MDW adalah direka berdasarkan kepada pengesanan seimbang berganda. Tesis ini menyediakan analisis matematik dan simulasi untuk menyiasat prestasi kod baru 2-D FCC-MDW. Gabungan domain panjang gelombang dan domain masa membawa kepada hak korelasi silang yang baik. Hasilnya, pengurangan MAI dengan bantuan reka bentuk penyahkod pengesanan keseimbangan berganda, penindasan PIIN boleh dicapai secara optimum. Penemuan yang paling jelas dari kajian ini adalah prestasi kod 2-D FCC-MDW mengatasi kod yang lain, iaitu 1-D FCC, 1-D MDW, 2-D perbezaan sempurna (PD) dan kod 2-D perbezaan cairkan sempurna (DPD) dari segi BER, kekardinalan, kuasa yang berkesan, kadar penghantaran data, kecekapan spektrum dan jarak fiber optik. Telah didapati bahawa cadangan kod baru mencapai kekardinalan tinggi dan berskala yang mana kod dicadangkan 2-D FCC-MDW mencapai 150 pengguna serentak pada BER 10^{-9} manakala kod 2-D PD dan kod 2-D DPD masing-masing hanya boleh mencapai 90 dan 135 pengguna serentak. Secara khususnya, kardinaliti kod 2-D FCC-MDW dapat menandingi kod PD 2-D dan 2-D kod DPD sebanyak 66.67% dan 11% masing-masing pada kadar data 622 Mbps. Kuasa berkesan minimum, P_{sr} bagi kod baru ini boleh dicapai pada -24dBm berbanding kod 2-D DPD yang memerlukan sebanyak -16dBm bagi merealisasikan keperluan penghantaran optik minimum. Secara keseluruhannya, 2-D FCC-MDW telah berjaya meningkatkan prestasi sistem secara keseluruhan. Penilaian dan pengesanan antara simulasi dan keputusan teori mendedahkan bahawa kod 2-D FCC-MDW dapat direalisasikan dalam rangkaian OCDMA.

Development of New Two Dimensional FCC-MDW Code with Wavelength / Time Scheme in Optical Code Division Multiple Access (OCDMA) Network Systems

ABSTRACT

A massive grown specifically for internet users worldwide encourages the service provider along with the researchers to explore an appropriate telecommunication technology that is beneficial to the users. Uniquely, as compared to other multiple access techniques, Optical Code Division Multiple Access (OCDMA) technique can be utilized in optical access network with full services on demand, such as internet protocol, video on demand, tele-presence and high quality audio. In spite of the robustness of OCDMA, the existence of Multiple Access Interference (MAI) and Phase Induced Intensity Noise (PIIN) in the system affects its performance. In fact, MAI is well known as a key factor of performance deterioration in the OCDMA system. For that reason, in this thesis, an investigation was conducted to explore on signature code that can minimize the MAI and PIIN. Another motivation of this study is to discover a signature code that can accommodate a huge number of simultaneous users which is in line with the recent demands. Consequently, two-dimensional (2-D) Flexible Cross Correlation-Modified Double Weight (FCC-MDW) code with Wavelength/Time (W/T) scheme is proposed and demonstrated. Basically, the construction of 2-D FCC-MDW code is formed by merging of two one-dimensional (1-D) OCDMA code known as 1-D FCC and 1-D MDW codes. The development of the code begins by assigning 1-D MDW code as a wavelength encoding pattern and 1-D FCC code sequences as time-spreading patterns. Furthermore, in order to mitigate MAI, the encoder and decoder of new 2-D FCC-MDW is designed based on double balanced detection. This thesis provides mathematical and simulation analysis in order to investigate the performance new 2-D FCC-MDW. The combination of wavelength domain and time domain leads to the good property of cross correlation. As a result, mitigation of MAI by the help of double balance detection decoder design, PIIN suppression can be achieved optimally. The most obvious finding to emerge from this study is that the performance of 2-D FCC-MDW code outperformed other codes, namely 1-D FCC, 1-D MDW, 2-D Perfect Difference (PD) code and 2-D Dilute Perfect Difference (DPD) code in terms of BER, cardinality, effective power, data transmission rate, spectral efficiency and fiber distance. It was found that the new proposed code achieves high cardinality and scalability whereby it attains 150 simultaneous users at the standard BER threshold of 10^{-9} while 2-D PD and 2-D DPD code can only achieve 90 and 135 simultaneous users respectively. Specifically, the cardinality of 2-D FCC-MDW code outshines the 2-D PD code and 2-D DPD code by the increment of 66.67% and 11% respectively at data rate 622 Mbps. The minimal effective power, P_{sr} of new proposed code can be achieved at -24dBm in comparison with 2-D DPD code requires -16dBm to realize the minimum optical transmission requirement. On the whole, 2-D FCC-MDW has been successfully improved the overall system performance. The evaluation and validation between simulation and theoretical results reveal that 2-D FCC-MDW code can be realized in the OCDMA network.

CHAPTER 1

INTRODUCTION

1.1 Demand for OCDMA Technology

Code division multiple access (CDMA) is originally based on the spread-spectrum communications used for military applications due to its inherent low probability of intercept. Later, this kind of multiple access is used in commercial mobile communications and satellite. Alternatively, optical CDMA (OCDMA) was introduced and fascinated the researchers due to its potential for enhancement in information security, improved spectral efficiency as well as increased flexibility of bandwidth (Shiraz & Karbassian, 2012). Recently, remarkable demand for multiple access has grown up, especially OCDMA for their flexibility and scalability (Kitayama Ken-ichi, 2014) albeit being outside the mainstream of optical communication research and development three decades ago. The key factor is due to the immaturity of optical devices which are proprietary to the OCDMA such as the optical en/decoder an optical thresholding device. However, with the amazing progress has been made in device technology, OCDMA becomes the promising multiple access technology for addressing the bandwidth and flexibility compared to other multiple access technology. As compared to others multiple access technologies, OCDMA technology can be utilized in optical access network with full services on demand, such as internet protocol, video on demand, tele-presence and high quality audio.

1.2 Problem Statement

The rise of the on-demand economy worldwide has massively grown specifically for internet users. There were 2.8 billion internet users as of 2014 compared to only 35 million users in 1995 or in percentage, 0.6 percent to 39 percent of the world's population (Gannes, 2015). The extreme increase in the percentage of internet users encourages the service provider and researcher to explore the appropriate telecommunication technology that is beneficial to the users. OCDMA is one of the multiple access technique that offers high security and large capacity since each data bit is sent as a sequence of optical pulses and the data will retrieve back at the receiving end by correlating the received signal with its own sequence. However, there is a large volume of published studies (Shiraz & Karbassian, 2012) describing that in the incoherent OCDMA system, the key factor of deterioration in the system performance is Multiple Access Interference (MAI). MAI is the hit probabilities between sequences that arise from dark pulses of interfering users, which replicate the signature sequence of the user (Sayed, Jolly & Khot, 2014). Noted that in the incoherent OCDMA system, various users with their specific and unique sequence can access the same channel simultaneously and asynchronously (Zhang, 2012). For that reason, the code sequences with good correlation properties or particularly with low cross-correlations need to be observed in order to minimize MAI.

The Spectral Amplitude Coding (SAC) technique was introduced to suppress the influence of the MAI effect by employing codes with fixed in-phase cross correlation, λ_c . Hence, several numbers of one dimensional (1-D) codes using SAC techniques have been proposed such as modified quadratic congruence (MQC) code (Wei & Shiraz, 2002), m-sequence code (Huang, 2006), MDW (Aljunid, Ismail, Ramli, Borhanuddin

& Abdullah, 2004) and ZCC (Anuar, Aljunid, Saad & Hamzah, 2009) to overcome the MAI effect from the system. However, the performance of the spectral-amplitude-encoding OCDMA system also is affected by the Phase Induced Intensity Noise (PIIN) (Shiraz & Kabassian, 2012). The incoherent lights are mixed and incident on the photo detector causes arise of PIIN. It should also be noted that the previous studies of 1-D codes revealed some other limitation such as a long code length of 1-D MDW and ZCC code resulting the increasing of MAI in the system. Previous researches have also shown that 1-D codes with good correlation properties still suffer from the low cardinality. Obviously, the cardinality or the number of users that can be supported affects the system capacity while the correlation properties of the signature codes can influence the BER of the system.

One of the promising solutions for this drawback is to employ two dimensional (2-D) code in OCDMA system. In 2-D encoding system, both, the flexibility of code design and the cardinality of the code can be improved significantly. The significant difference about the 2-D optical CDMA system from the 1-D counterpart is that every pulse in the spreading codeword is transmitted at a unique wavelength (Ni, 2005). In order to match the transmitter in frequency domain, each delay line at the receiver is equipped with a band-pass filter (BPF) to allow only a specific wavelength go through. Hence, the intention of this research is to propose the 2-D code with good correlation properties by using W/T method as well as to demonstrate this 2-D code has good code cardinality with satisfactory performance. The relevance of correlation properties of the system performance, especially the Bit Error Rate (BER) is very clear. A little difference in average hit probability of pulses between different sequences will result in visible improvement in BER (Zhang, 2012). In other words, BER, cross correlation and cardinality are interrelated to each other. Furthermore, Prucnal (2006) highlighted the

advantage of 2-D W/T schemes that offer the scalability and flexibility as well as provides a lower probability of interception.

1.3 Research Objectives

This research was undertaken to present a new 2-D OCDMA coding system that can enhance the system performance as well as the cardinality of the OCDMA network. The primary aim of this research is to design a spreading code with significant correlation properties to suppress MAI effectively. This new 2-D signature code is developed by combining of two 1-D code (1-D MDW and 1-D FCC codes), namely 2-D FCC-MDW. Particularly, the objectives of this research covers:

- Development of 2-D FCC-MDW code with W/T scheme in OCDMA system.
- Analyze the theoretical performance and simulated performance of proposed 2-D FCC-MDW code as well as comparing its system performance with the existing similar structured codes at the standard BER.
- Validate the proposed 2-D FCC-MDW code by comparing the results from the mathematical derivation and simulation data.

1.4 Scope of Works

The scope of this study involves with the capability of 2-D code by using W/T methods to suppress the influence of the MAI effect in the incoherent SAC-OCDMA system. A number of studies have examined the relationship between the MAI effect and the degradation of system bit error rate (BER) (Shiraz & Karbassian, 2012; Yin & Richardson, 2007). This newly proposed 2-D signature code can be obtained by

combining of 1-D MDW (Aljunid *et. al.*, 2004) and 1-D FCC (Rashidi, Aljunid, Ghani, Fadhil, Anuar, & Arief, 2014) codes known as 2-D FCC-MDW. The scheme used is based on wavelength and time encoding decoding process. Each user will be assigned a hybrid signature code where the optical pulses will be first encoded in the wavelength domain using MDW code scheme and later the FCC code will be encoded in the time domain. The serious issues to deal with when designing the code in OCDMA system with satisfactory performance is that the correlation properties and the number of users can be supported (Chen, 2007). Hence, to demonstrate the potential of this approach and its suitability for the application, the mathematical derivation is investigated. A simulation which uses OPTISYS simulation software Version 7.0 used to simulate the data which practically replicate a real system. The comparison will be carried out between the theoretical (mathematical analysis) and simulation data. In order to verify the analytical methods, all the mathematical development based on 2-D FCC-MDW code will be compared with the existing similar structured 2-D codes.

1.5 Research Contribution

The important contributions drawn from this research include:

- i) A new mathematical algorithm of the SNR and BER for 2-D OCDMA code system by employing wavelength-time technique/scheme was developed.
- ii) A new 2-D FCC-MDW code in OCDMA was thoroughly analyzed and compared with existing 2-D code.
- iii) New design of encoder-decoder for a 2-D OCDMA network system based on the double balanced detection scheme is developed.

- iv) Realization of new 2-D OCDMA system of high capacity transmission on optical platform.

1.6 Thesis Structure

This thesis focuses on developing a new theoretical algorithm and simulation techniques to enhance the performance and cardinality in OCDMA networks. A 2-D spreading sequence is proposed for OCDMA systems by employing the wavelength-time scheme. In particular, the 2-D FCC-MDW algorithm not only comparable performance with other existing systems, but it allows an increased number of simultaneous users to be generated. It begins with demands of OCDMA technology in the current trend of telecommunications system. The challenges of OCDMA system that clarify the motivating aspect together with the objectives of this research, scope of work and research contribution are included in Chapter 1.

Chapter 2 will present the background of OCDMA in a multiple access scheme, the progress of OCDMA technology during the past three decades and the classification of OCDMA system.

Chapter 3 provides the methods used to design and analyze the 2-D incoherent OCDMA codes. The principal aims to provide the general overview required to understand some mathematical theory of the other existing 2-D code sequences in OCDMA system. Moreover, the parameters used for analyzing the performance of 2-D code sequences are also presented. Together with this, it is an introduction to the OptiSystem simulator package as a simulation tool in this research.

Chapter 4 presents the explicit constructions of new 2-D FCC-MDW code sequences based on the combination of 1-D FCC and 1-D MDW codes. Derivation of a